


INSTALLATION INSTRUCTIONS

for the

Kodak MINILOADER 2 PLUS



Use this Publication for:-

MINILOADER 2 Plus Model Stand-alone (SV code 3236), MINILOADER 2 Plus Model M35-M (SV code 3239) and MINILOADER 2 Plus Model 480RA (SV code 3240).



HEALTH SCIENCES DIVISION

CAUTION

This equipment includes parts and assemblies sensitive to damage from electrostatic discharge. Use caution to prevent damage during all service procedures.

PLEASE NOTE

The information contained herein is based on the experience and knowledge relating to the subject matter gained by Kodak Ltd. prior to publication.

No patent licence is granted by this information.

Kodak reserves the right to change this information without notice, and makes no warranty, express or implied, with respect to this information. Kodak shall not be liable for any loss or damage, including consequential or special damages, resulting from the use of this information, even if loss or damage is caused by Kodak's negligence or other fault.

CONTENTS

	PAGE
UNPACKING AND INSTALLATION INSTRUCTIONS FOR M35-M VERSION	4
UNPACKING AND INSTALLATION INSTRUCTIONS FOR 480RA VERSION	1 3
UNPACKING AND INSTALLATION INSTRUCTIONS FOR STAND-ALONE VERSION	1 6
MAMMOGRAPHY CASSETTE PREPARATION	2 0
VIDEO CASSETTE PREPARATION	2 1
INSTALLATION CHECK LIST	2 2
APPENDIX "A" - SUITABLE STANDS	2 6
PUBLICATION CHANGE NOTE TABLE	2 9


UNPACKING AND INSTALLATION INSTRUCTIONS FOR M35-M VERSION.

NOTE :- A 5 or 6 amp fused supply should be provided for the MINILOADER.

1. The MINILOADER is in the smaller of the two PACKING CASES, the larger CASE contains the STAND for the MINILOADER and the parts for the M35-M.
2. Remove the BANDING from the larger PACKING CASE and lift the CARTON off the PALETTE.
3. Unpack and check all the parts. The CASE should contain :-


PART	QUANT.	DESCRIPTION
30015562	8	COUNTERSUNK SCREWS M4x12 - (FOR PROCESSOR PANEL FIXING)
30015569	1	PLAIN WASHER M4 - (LEFT HAND PROCESSOR PANEL FIXING)
30015612	2	NUT M4 - (LEFT HAND PROCESSOR PANEL FIXING)
30015655	4	SCREW, HEXAGONAL, M8x20 - (FASTENING MINI. TO THE STAND)
30015669	2	STAR WASHER M4 - (FAN GRID GROUNDING)
30015691	1	SCREW M4x12 - (LEFT HAND PROCESSOR PANEL FIXING)
30025836	4	STAR WASHER M10 - (USED TO GROUND M35-M TO PLINTH)
30025838	4	STAR WASHER M8 - (USED TO GROUND MINILOADER TO STAND)
30025842	7	CUP WASHER M4 - (FOR PROCESSOR PANEL FIXING)
30025843	8	CAGED NUT M4 - (FOR PROCESSOR PANEL FIXING)
30026148	1	STAND ASSY. - (FOR MINILOADER)
30026149	1	FRONT PANEL ASSY - M35-M
30026151	1	REAR PANEL ASSEMBLY - M35-M (INCLUDES 30026153 & 30026157)
30026155	1	DRIER EXIT PLATE - M35-M
30026162	1	PLINTH - M35-M
30026172	6	RETAINING BLOCKS
30026180	1	PROCESSOR LIGHT BAFFLE
30026205	1	M35-M TRANSPARENT PANEL - LEFT
30026206	1	M35-M TRANSPARENT PANEL - RIGHT
30026252	1	M35-M TRANSPARENT PANEL - FRONT
30025253	1	M35-M FAN GRID
30026254	1	BRACKET, M35-M TRANSPARENT PANEL RIGHT, RETAINING
30026255	1	PLATE, M35-M MAINS SWITCH PROTECTING

4. In the position where the MINILOADER is to stand, (the rear of the STAND is the open end), level the STAND using the JACKING SCREWS leaving a gap of approximately 15 mm between the floor and the bottom of the STAND. See FIGURE 1.
5. Unpack the M35-M PROCESSOR, remove the LID, FRONT PANEL, and the two SIDE PANELS. Unscrew the STAND-BY OVERRIDE BUTTON from the REAR PANEL (leave the wires connected). Remove the REAR PANEL, disconnecting the EXHAUST HOSE from the EXHAUST ADAPTOR. Remove the EXHAUST ADAPTOR, and the PANEL FIXING SCREWS and RETAINING WASHERS from the REAR PANEL and keep. Discard all PANELS.




6. Place the PROCESSOR PLINTH (the PLINTH is symmetrical, it can be either way round) in position under the STAND. Roll the MINILOADER STAND away and install the FLOOR PLATES supplied with the PROCESSOR under the LEVELLING FEET, and level the PLINTH leaving a gap of approximately 25 mm between the floor and the bottom of the PLINTH. See FIGURE 2.

Figure 2



7. Roll the STAND away and install the PROCESSOR on the PLINTH, the front of the PROCESSOR towards the front of the STAND, and secure it using the SCREWS supplied with the PROCESSOR and the M10 STAR WASHERS supplied in the kit. See FIGURE 3. IMPORTANT, MAKE SURE THERE IS NO PAINT ON THE PROCESSOR PLINTH WHERE THE STAR WASHERS CONNECT.

FIGURE 3


8. Remove the BANDING from the smaller PACKING CASE then lift the CARTON off the MINILOADER PALETTE.
9. Remove the MAGAZINES from the top of the MINILOADER and unpack them.
The case should contain:-

PARTNo.	QUANT	DESCRIPTION
xxxxxxx	1	MINILOADER 2 PLUS M35-M VERSION
30023169	1	SUPPLY MAGAZINE 18x24 CM
30023168	1	SUPPLY MAGAZINE 24x30 CM
30026197	1	SUPPLY MAGAZINE 8x10 INCH
30023197	1	SERIAL UNLOADING MAGAZINE 18x24 CM
30026262	1	SERIAL UNLOADING MAGAZINE 24x30 CM
30025844	2	KEYS FOR INTERLOCK OVERRIDE (INSIDE MINILOADER)
30025849	1	CAN OF TOUCH-UP PAINT
30026265	1	PIN 6 x 35 MM (INSIDE MINILOADER)

10. Remove the LID and lift the MINILOADER onto its STAND. The front of the MINILOADER is at the front of the STAND. IMPORTANT - ONLY LIFT THE MINILOADER BY THE FRAME AS SHOWN IN FIGURE 4.


!! CAUTION TWO PEOPLE ARE REQUIRED TO LIFT THE MINILOADER !!

Figure 4




11. Secure the MINILOADER on it's STAND using the four socket head SCREWS and M8 STAR WASHERS supplied with the STAND. IMPORTANT - ENSURE THERE IS NO PAINT ON THE STAND WHERE THE STAR WASHERS CONNECT.
12. Remove the left hand SIDE PANEL from the MINILOADER.
13. Remove the following PACKING PROTECTIONS :-
 - a) The two RUBBER TIES that restrain the two SUCKER BARS.
 - b) The packing BLOCKS under the TWO SUCKER BARS.
 - c) The protection PACKING from the film exit CHUTE.
 - d) The TIE-WRAP from the MAGAZINE INJECTOR BAR.
 - e) The TIE from the CASSETTE INJECTOR.
14. Remove the BAG containing the SERVICE KEYS and the ZERO POSITION PEG.

15. Mount the six aluminium RETAINING BLOCKS on the top of the PROCESSOR FRAME as shown in FIGURE 5.




16. Refit the EXHAUST ADAPTOR (removed in step 5) to the new PROCESSOR REAR PANEL using the existing HARDWARE. Fit the new REAR PANEL to the PROCESSOR using the original SCREWS etc. Connect the EARTH LEAD from the PANEL to the M35-M ELECTRICAL BOX as shown in FIGURE 6. Refit the STAND-BY/RUN SWITCH. Reconnect the M35-M EXHAUST HOSE to the EXHAUST ADAPTOR.

Figure 6




17. Remove the TOP and BOTTOM COVERS from the M35-M DRIER ASSEMBLY and retain. Remove the EXIT PLATE from the DRIER ASSEMBLY and keep one of the longer SCREWS (8/32 UNC x 5/8"). Discard the EXIT PLATE and the other SCREWS. Fit the new EXIT PLATE supplied using the five new SCREWS and the one retained SCREW. See FIGURE 7.

Figure 7




18. Complete all the PLUMBING and WIRING to the PROCESSOR. See FIGURE 8 for the purpose of the HOLES in the REAR PANEL.

Figure 8



19. Discard the parts shown in FIGURE 9, but replace the CLIP which retains the ACCESS PANEL in place.

Figure 9



20. Fit the FAN GRID, using the original SCREWS, but adding the M4 STAR WASHERS. IMPORTANT - THE PAINT MUST BE REMOVED FROM THE FRAME WHERE THE STAR WASHERS CONTACT IT. See FIGURE 10.




Figure 10

21. Fit the PROCESSOR protection PANELS as shown in FIGURES 11, 12 & 13.

Mount the eight M4 CAGED NUTS (30025843) in the eight holes in the PROCESSOR FRAME where indicated (removing old SPEED NUTS where necessary) and fasten the new clear PANELS and new METAL BRACKETS using the M4 COUNTERSUNK SCREWS (30015562) and CUP WASHERS (30025842). Also make the other fastenings as shown in the Figures.

Figure 11




Figure 12






Figure 13.

22. Position the MINILOADER and STAND in front of the M35-M. Pull the Miniloader over the PROCESSOR (lifting it slightly to clear the STOPS). Fasten the CABLE RETAINING BLOCK to the PROCESSOR REAR PANEL using the SCREWS provided. See FIGURE 14. Check that the CABLE is not strained when the MINILOADER is pulled forward to its STOPS. Lay the LIGHT BAFFLE in position on the top of the PROCESSOR. Plug in the two FLYING LEADS for PHOTOCCELL FC9 and STAND-BY OVER-RIDE. Pull the MINILOADER into its fully docked position and ensure the relative heights of the MINILOADER and PROCESSOR are correct. Adjust if necessary.

Figure 14

23. Complete the installation of the M35-M PROCESSOR, using the M35-M INSTALLATION MANUAL. **IMPORTANT, THE M35-M MUST BE INSTALLED IN ACCORDANCE WITH THE M35-M INSTALLATION MANUAL AND ADDITIONALLY IN ACCORDANCE WITH LOCAL PRACTICES.** Then go to the INSTALLATION CHECK LIST on page II-22 of this PUBLICATION.

UNPACKING AND INSTALLATION INSTRUCTIONS FOR 480RA VERSION.

1. Remove the BANDING from the PACKING CASE then lift the CARTON off the MINILOADER PALETTE.
2. Remove the MAGAZINES from the top of the MINILOADER and unpack them.

The case should contain:-

PARTNo.	QUANT	DESCRIPTION
xxxxxxx	1	MINILOADER 2 PLUS VERSION 480RA
30023169	1	SUPPLY MAGAZINE 18x24 CM
30023168	1	SUPPLY MAGAZINE 24x30 CM
30026197	1	SUPPLY MAGAZINE 8x10 INCH
30023197	1	SERIAL UNLOADING MAGAZINE 18x24 CM
30026262	1	SERIAL UNLOADING MAGAZINE 24x30 CM
30015540	2	SCREW, M4 x 30 (USED TO FASTEN MINILOADER TO PROCESSOR)
30015564	2	NUT, M4 (USED TO FASTEN MINILOADER TO PROCESSOR)
30015612	2	NUT, THIN, M4 (USED TO FASTEN MINILOADER TO PROCESSOR)
30025844	2	KEYS FOR INTERLOCK OVERRIDE (INSIDE MINILOADER)
30025845	4	LARGE DIAMETER WASHER M4 (USED TO FASTEN MINI TO PROC)
30025846	4	SCREW, HEXAGON HEAD, M8 x 40 (MINILOADER LEVELLING FEET)
30025848	4	WASHER, FLAT, M8
30025849	1	CAN OF TOUCH-UP PAINT
30026265	1	PIN 6 x 35 MM (INSIDE MINILOADER)


3. Fit the four LEVELLING SCREWS (30025846) to the tapped HOLES in the BASE of the MINILOADER.
4. Remove the LID and lift the MINILOADER onto its STAND. Drawings of suitable STANDS are shown in APPENDIX "A".

!! CAUTION TWO PEOPLE ARE REQUIRED TO LIFT THE MINILOADER !!


5. If the STAND is metal, an earth connection must be made between the STAND and the MINILOADER.. IMPORTANT - ENSURE THE PAINT IS REMOVED WHERE THE EARTH CONNECTION IS MADE.
7. Remove the left hand SIDE PANEL from the MINILOADER.

8. Remove the following PACKING PROTECTIONS :-
 - a) The two RUBBER TIES that restrain the two SUCKER BARS.
 - b) The packing BLOCKS under the TWO SUCKER BARS.
 - c) The protection PACKING from the FILM EXIT CHUTE.
 - d) The TIE-WRAP from the MAGAZINE INJECTOR BAR.
 - e) The TIE from the CASSETTE INJECTOR.
9. Remove the BAG containing the SERVICE KEYS and the ZERO POSITION PEG.
10. In the two HOLES under the PROCESSOR FEED SLOT marked "X", install the two SCREWS M4 x 30, and the two THIN M4 NUTS as shown below in figure 15. Place one of the M4 LARGE DIAMETER WASHERS on each SCREW.


Figure 15



11. Align the MINILOADER and PROCESSOR horizontally as shown in figure 16, fit the other two M4 LARGE DIAMETER WASHERS and the M4 NUTS. Do not tighten the NUTS yet. It is very important to have the alignment correct, especially for an RA PROCESSOR because the CHUTE EXTENSION can interfere with the LED's inside the FILM ENTRY.

Figure 16

12. By adjusting the LEVELLING SCREWS on the MINILOADER, (and the PROCESSOR if necessary), set the height of the MINILOADER. The vertical alignment is correct when a FILM hits the lower ENTRY ROLLER 1.5 mm below the nip of the ROLLERS. See figure 17.

Figure 17

13. When both horizontal and vertical alignments are correct, tighten the M4 NUTS.
14. Go to the INSTALLATION CHECK LIST on page II-22 of this publication to complete the installation..

UNPACKING AND INSTALLATION INSTRUCTIONS FOR STAND-ALONE VERSION.


1. Remove the BANDING from the PACKING CASE then lift the CARTON off the MINILOADER PALETTE.
2. Remove the MAGAZINES from the top of the MINILOADER and unpack them.
The case should contain:-

PARTNo.	QUANT	DESCRIPTION
xxxxxxx	1	MINILOADER 2 PLUS STAND-ALONE VERSION
30023169	1	SUPPLY MAGAZINE 18x24 CM
30023168	1	SUPPLY MAGAZINE 24x30 CM
30026197	1	SUPPLY MAGAZINE 8x10 INCH
30026239	1	RECEIVING MAGAZINE 18x24 CM
30026240	1	RECEIVING MAGAZINE 24x30 CM / MIXED SIZES
30025844	2	KEYS FOR INTERLOCK OVERRIDE (INSIDE MINILOADER)
30025845	4	LARGE FLAT WASHERS, INTERNAL DIAMETER 8 MM
30025846	4	SET SCREW, HEXAGON HEAD, M8 x 40 MM
30025847	4	SET SCREW, HEXAGON HEAD, M8 x 60 MM
30025849	1	CAN OF TOUCH-UP PAINT
30026265	1	PIN 6 x 35 MM (INSIDE MINILOADER, PACKED WITH THE KEYS)

3. Remove the LID and lift the MINILOADER onto a suitable STAND or BENCH. See figure 18 for details of the holes required in the STAND or BENCH to secure the MINILOADER. See APPENDIX "A" for drawings of suitable STANDS

!! CAUTION TWO PEOPLE ARE REQUIRED TO LIFT THE MINILOADER !!

Figure 18



4. Secure the MINILOADER on its STAND using four of the supplied HEXAGON HEADED SCREWS (use the most appropriate length SCREW 40 or 60 mm to suit the thickness of the BENCH top). If desired also use the large flat WASHERS (supplied) under the HEADS of the SCREWS. Using the large WASHERS means that the locating holes can be made larger and do not need to be as accurately drilled.

If the STAND is metal, M8 STAR WASHERS should be used to make sure the STAND is earthed.
IMPORTANT - ENSURE THERE IS NO PAINT ON THE STAND WHERE THE STAR WASHERS CONNECT.

5. Remove the left hand SIDE PANEL from the MINILOADER.
6. Remove the following PACKING PROTECTIONS :-
 - a) The two RUBBER TIES that restrain the two SUCKER BARS.
 - b) The packing BLOCKS under the TWO SUCKER BARS.
 - c) The TIE-WRAP from the MAGAZINE INJECTOR BAR.
 - d) The TIE from the CASSETTE INJECTOR.
7. Remove the BAG containing the SERVICE KEYS and the ZERO POSITION PEG.
8. There are two methods of collecting exposed FILMS in the STAND -ALONE MINILOADER.
 - i) 18 x 24 and 24 x 30 mammography FILMS are collected in separate RECEIVING MAGAZINES which the OPERATOR changes when they change size. This is the default configuration. If this is the configuration you require, fix the "24 x 30" LABEL and REFLECTIVE PATCH (packed inside the 24 x 30 RECEIVING MAGAZINE) to the MAGAZINE, see figure 19. Then go to the INSTALLATION CHECK LIST on page II-22 of this publication.
 - ii) All sizes, 18 x 24 & 24 x 30 mammography FILMS and 8 x 10 inch video FILMS are collected in one RECEIVING MAGAZINE. Note :- If the MINILOADER is set up in this way, the RECEIVING MAGAZINE cannot subsequently be unloaded by a MINILOADER using SERIAL MODE. If this is the configuration you require, proceed as follows.
9. Fix the LABEL "CAUTION!
RECEIVING MAGAZINE ONLY
CANNOT BE UNLOADED BY A MINILOADER"

which is packed inside the 24 x 30 RECEIVING MAGAZINE onto the outside of the MAGAZINE over the existing LABEL.

Do not fix the "24 x 30" LABEL or the REFLECTIVE PATCH to the MAGAZINE.

Figure 19


Change this label to

"CAUTION

RECEIVING MAGAZINE ONLY

CANNOT BE UNLOADED BY A MINILOADER"


*when all films are being
collected in single magazine*




10. PHOTOCELL FC7 must be moved so it detects the MAGAZINE FULL PATCH at the HINGE end of the RECEIVING MAGAZINE. See figure 20.

*Original position of FC7 for
separate collection of films*

*New position of FC7 for collection
of all films in one magazine*


Figure 20

Unscrew the PHOTOCELL and move it to the opposite end of the mounting bracket. See figure 21. Remember to adjust the PHOTOCELL to give correct MAGAZINE FULL detection as you complete the installation.


**Figure 21**

11. The DIPSWITCH on PCB 301 must be altered as shown below so the PROGRAM knows which system of collecting the FILM is in operation. See figure 22.


Figure 22



ALL FILM SIZES COLLECTED
IN THE SAME RECEIVING
MAGAZINE



18 x 24 & 24 x 30 FILMS
COLLECTED SEPARATELY



12. Go to the INSTALLATION CHECK LIST on page II-22 of this publication to complete the installation.

MAMMOGRAPHY CASSETTE PREPARATION.

All MINILOADER CASSETTES must be patched correctly otherwise reliable operation is impossible. The CASSETTES should be patched as shown below using TOOLS 9194531 & 9194511. The correct PATCHES are PART NUMBER 9194551, REFLECTIVE FOIL 8 x 15 mm. Place 3 PATCHES (8 x 15 mm) as shown in figures 23 and 24, using the TOOLS as indicated.

If MODIFICATION 2 is active, no MAMMOGRAPHY CASSETTES should have a second (TYPE 2) patch.

This is the TYPE 2 position.





Figure 23

Figure 24




VIDEO CASSETTE PREPARATION.

All MINILOADER CASSETTES must be patched correctly otherwise reliable operation is impossible.


The correct PATCHES are PART NUMBER 9194551, REFLECTIVE FOIL 8 x 15 mm. Fit one PATCH as shown below in figure 25. If MODIFICATION 2 is active, fit a second PATCH on the opposite side. There are no PATCHES inside VIDEO CASSETTES.

Figure 25



To prevent FILMS sticking to the FRAME of the VIDEO FILM HOLDER, self adhesive FELT PADS can be attached to the FRAME. The FELT PADS need to be cut to a length of 6 mm and fastened to the CASSETTE as shown below in figure 26. There are ten FELT PADS in a kit, and they are supplied with installation instructions.

The part number of the FELT PAD KIT is 9166451.



CHECK LIST FOR COMPLETING THE INSTALLATION.

NOTE :- Remember that any adjustments, part replaced etc. should not be fed back as PURPOSE CODE XN.
The correct feedback code for the problem solved should be used.

Check the modification status of the MINILOADER 2 PLUS. Order any type 1 required modifications necessary. Check the SOFTWARE is the latest version, and the correct language variant for your country is fitted. All MINILOADERS are delivered with language variant 1 - See TABLE.

MINILOADER VERSION	LANGUAGE	VARIANT	CAT NO.	PART NO.
Stand-Alone	English/Swedish	1	No Cat No.	30025870
Stand-Alone	T.B.D.	2	T.B.D.	T.B.D.
Processor Interface	English/German	1	No Cat No.	30025871
Processor Interface	English/Italian	2	719 0974	30025872
Processor Interface	English/Spanish	3	713 1489	30025873
Processor Interface	English/Swedish	4	713 1477	30025874
Processor Interface	English/Portugese	5	713 1519	30025875
Processor Interface	English/Norwegian.	6	713 1527	30025876
Processor Interface	English/French	7	T.B.D.	30025869

If the MAINS PLUG is fused, a 5 Amp fuse should be fitted, otherwise the socket the MINILOADER is plugged into should be protected by a 5 or 6 Amp fuse. If the MINILOADER is powered from the PROCESSOR, the PROCESSOR should be modified to provide a fused supply. Follow local practice and regulations.

1. Check that the voltage tappings of the two TRANSFORMERS in the MINILOADER are set to the correct supply voltage.

Supply voltage 210 - 229 volts	use 220 volt tappings.
Supply voltage 230 - 250 volts	use 240 volt tappings.


2. Connect power to the MINILOADER.

IMPORTANT

The wires in this mains lead are coloured in accordance with the following code:

GREEN AND YELLOW	- EARTH
BLUE	- NEUTRAL
BROWN	- LIVE

As the colours of the wires in the mains lead of this appliance may not correspond with the coloured markings identifying the terminals in your plug proceed as follows:

The wire coloured green and yellow must be connected to the terminal on the plug marked with the letter E or by the earth symbol  or coloured green or green-and-yellow.

The wire coloured brown must be connected to the terminal marked with the letter L or coloured red.

The wire coloured blue must be connected to the terminal marked with the letter N or coloured black.

3. Put one of the SERVICE KEYS into the KEY-SWITCH and turn the SWITCH on. Turn the MINILOADER MAIN SWITCH on.
The DISPLAY should read "PLEASE WAIT-RESET OPERATING" and the ORANGE LIGHT should be on. The CAM MOTOR should run until the "home" position is reached, then the ALARM will sound, the RED LIGHT will come on and the message "MAGAZINE 18*24 NOT IN CORRECT POSITION" will be displayed.
Press the RESET BUTTON twice (the first press silences the ALARM and the second press cancels the message). The GREEN LAMP should come on and the DISPLAY should read "MINILOADER READY FOR FORMAT 18*24".
If the MINILOADER does not operate correctly, consult the SERVICE MANUAL.
4. Open the FRONT DOOR and install the 24 x 30 cm MAGAZINE, loaded with TEST FILM, into the lower MAGAZINE TRAY.
Press the SIZE CHANGE BUTTON once. The DISPLAY will read "CHANGING FORMAT", the ORANGE LIGHT will come on, and the MAGAZINE CARRIAGE will take the 24 x 30 MAGAZINE to the rear position. The GREEN LIGHT will come on, and the DISPLAY will read "MINILOADER READY FOR FORMAT 24*30".
Install the 18 x 24 cm MAGAZINE, loaded with TEST FILM into the upper MAGAZINE TRAY. Close the FRONT DOOR. The MINILOADER is now ready for testing.
5. Check the PUSH RODS etc. for tightness.
6. Clean the SUCKERS by rubbing them with grade 200 EMERY CLOTH, or a similar material, and dust them with NATURAL TALCUM POWDER. If the surface of the SUCKERS is subsequently touched, this procedure must be repeated.
7. Vacuum out the MINILOADER 2 PLUS to remove any dust.

8. Fit the STEP-BY-STEP SWITCH, run a cycle with each size of film and check the SUCKER VACUUM is between 150 & 200 millibar. Adjust if necessary.
Check the COMPRESSOR reaches a minimum pressure of 2.0 bar. Correct if necessary.
9. Run several cycles with each available size of TEST FILM, checking for correct TILT operation, good FILM separation in the SUPPLY MAGAZINE, correct insertion of FILMS into the CASSETTES and correct delivery of FILM into the CHUTE (or RECEIVING MAGAZINE, depending on version of MINILOADER). Make any adjustments necessary.
10. Using an 18 x 24 or 24 x 30 CASSETTE, stick a FILM to the SCREEN, enter the CASSETTE and make sure the FILM is detected by PHOTOCCELL FC4. Check that the CASSETTE INJECTOR is blowing in the correct place to remove the film from the SCREEN.
11. Check the operation of all other PHOTOCCELLS. If the MINILOADER is a STAND-ALONE unit, remember to check the RECEIVING MAGAZINE full setting (80 to 90 FILMS).
12. Check the operation of the OPERATOR KEYPAD, the LIGHT BAR and the DISPLAY.
13. Check the settings of the PARAMETERS, see TABLE. Also see the THEORY GUIDE for a full description of the PARAMETERS and details of how to set them.
NOTE :- If the MINILOADER is interfaced to a PROCESSOR, you must set the PARAMETER P4 "GAP BETWEEN FILMS" to suit the speed of the PROCESSOR being used.
IMPORTANT :- If the PROCESSOR has adjustable speeds which can be selected by the OPERATOR, the PARAMETER must be set to suit the slowest speed being used.


PARAMETER	DESCRIPTION	STANDARD VALUE (SECS)	RANGE (SECS)
P1	Cassette air blow pause	1.5	1.5 - 3.5
P2	Magazine film separation blow pause	1.5	1.5 - 3.5
P3	Multiple film load detector pause	0.5	0.3 - 2.8
P4	Gap between films	Depends on processor	0.0 - 20.0
P5	Tilt pause	2.0	1.5 - 3.5


14. Check that the PROCESSOR (if fitted) is brought out of stand-by when a CASSETTE is entered in the MINILOADER.
15. Set the date and time on the MICROPROCESSOR (see the THEORY GUIDE). Zero all statistics and film counters (operator and ESR).
16. Remove the STEP-BY-STEP SWITCH and the SERVICE KEY and re-install all the PANELS.
17. Load the MINILOADER 2 PLUS with some customer FILM and make some test cycles. Examine the processed film for artifacts such as scratches, SUCKER marks and light fog. Correct as necessary. If the MINILOADER is a STAND-ALONE unit, if possible take the film elsewhere to process and do the checks.
18. Fill in the INSTALLATION REPLY FORM, and note the meter (counter) reading. Make sure the correct SERVICE CODE is used when feeding back the installation to SCAN.

SERVICE CODE	MODEL
3236	STAND-ALONE
3239	M35-M
3240	480RA

APPENDIX "A"

The STAND shown here is suitable for use with a model 480RA MINILOADER interfaced to a M6B / 460RA / 480RA PROCESSOR. With adaption it could be used for a STAND-ALONE MINILOADER. If used for a STAND-ALONE MINILOADER, it would be necessary to drill four HOLES as shown in figure 18 (page II-16) in the TOP to bolt the MINILOADER to the STAND.






CONSTRUCTION IN 25 mm MELAMINE FACED LAMINATED BOARD

ALL DIMENSIONS IN MILLIMETRES - NOT TO SCALE - DO NOT SCALE FROM DRAWING

The stand shown below would be suitable for a STAND-ALONE MINILOADER. The addition of a solid TOP would reduce the noise caused by vibration. The use of some sound insulation material between the TOP and the MINILOADER would further reduce the noise.



ALL DIMENSIONS ARE IN MILLIMETRES - NOT TO SCALE - DO NOT SCALE.

The CASTORS should be adjustable for height and should be capable of carrying a load of 50 Kg each. All construction should be painted steel.

This design is not suitable for a PROCESSOR INTERFACE MINILOADER.

Publication change Notice Table

Rev. Date	PCN No.	Pub.No.	Affected Pages	Description
December 92	1	30080004	All	Complete updating of all pages and addition of Installation instructions for Models Stand-Alone and 480RA



HEALTH SCIENCES DIVISION
