



SERVICE BULLETIN

KODAK X-OMAT Processor

Eastman Kodak Company/Customer & Technical Services/Health Sciences Markets Division/Rochester, New York 14650

SERVICE BULLETIN NO. 201

Revised September 1994
Supersedes August 1994

NOTE

This Service Bulletin was revised to clarify the *Kodak X-Omat* 460 RA Processor Serial Number range. The *Kodak X-Omat* 460 RA Processor information is unchanged.

Kodak X-Omat 460 RA PROCESSOR **Kodak X-Omat 270 RA PROCESSOR**

Verify Installation of Modification No. 1 on the *Kodak X-Omat* 460 RA Processors

From field problem reports, it is apparent that not all 460 RAs have been updated with Modification No. 1. The purpose of this Service Bulletin is to reinforce the importance of this modification. You should verify that all 460 RAs that you service have had this modification. Modification No. 1 is Type 1, Mandatory.


Mod. No.	Part No.	Serial Nos.	Purpose	Date Available
1	MA3056-9	633 and below except for Serial No. 610, 620, 622, 624, and 628 - 631	This modification must be completed to prevent Connector P/J 502 from overheating. Overheating could cause an overcurrent and heating condition that will destroy the 500 Circuit Board and Connector. (Cable Connector Part No. 335500)	6/91

Verify Installation of Modification No. 8 on the *Kodak X-Omat* 270 RA Processors

From field problem reports, it is apparent that not all Kodak X-Omat 270 RA Processors have been updated with Modification No. 8. A possibility also exists that Processors above serial number ranges stated in the modification instructions for Modification No. 8 may not have had these modifications factory installed.

The purpose of this Newsletter is to reinforce the importance of these modifications. Modification No. 8 is Type 1 Mandatory. If these modifications are not installed, severe damage to the 500 CIRCUIT BOARD and/or ELECTRICAL BOX may result.

On your next scheduled visit, for all 270 RA Processors **with a serial number below 500**, verify the installation of Modification No. 8. Check that the RELAY K1 has been installed in the ELECTRICAL BOX. If the K-1 RELAY has not been installed, order modification No. 8, Part No. 981876 and install it in the processor.



H104_0348BCC
H104_0348BA

Mod. No.	Part No.	Purpose
8	981876	To provide Dryer Over Temperature protection and prevent the failure of the J502 Connector. (Connector Part No. 335500)

For more information, please contact:

Eastman Kodak Company
Imaging Service Center
Health Sciences Division
100 Carlson Road
Rochester, New York 14653-9013
(716) 724-1789, Option 1

Please be prepared to give your Service Customer Number and your equipment serial number.

svcbul_201.txt
N-913

Kodak and X-Omat are trademarks.

