

MODIFICATION INSTRUCTIONS

for the

KODAK MULTILOADER 700

Service Code 3053

Modification No. 20

TYPE 1 REQUIRED

PURPOSE:

To ensure that flooding of the HUMIDIFIER does not cause damage to the ML700

SERIAL NUMBERS:	all SN < 1570 (50Hz) all SN < 5336 (60 Hz)
INSTALLATION TIME:	Approx. 0.5 hour
SPECIAL TOOLS:	ELECTRIC DRILL 10 mm DRILL BIT
PARTS REQUIREMENTS:	Modification Kit 9195016

PLEASE NOTE

The information contained herein is based on the experience and knowledge relating to the subject matter gained by Kodak prior to publication.

No patent license is granted by this information.

Kodak reserves the right to change this information without notice, and makes no warranty, express or implied, with respect to this information. Kodak shall not be liable for any loss or damage, including consequential or special damages, resulting from the use of this information, even if loss or damage is caused by Kodak's negligence or other fault.

PARTS LIST

<u>PART-NO.</u>	<u>DESCRIPTION</u>	<u>QUANTITY</u>
9195016.....	MOD KIT 20	

The KIT contains:

9195011.....	COVER PLATE.....	1
5007128.....	VELCRO STRIP 6 cm	1
5554501.....	WIRE TIE	1

INTRODUCTION

If the HUMIDIFIER is flooded, the water entering the ML700 is drained through a hole in the BASE PLATE. In addition PCB A16 is moved from the BASE PLATE to a higher position.

INSTALLATION

- 1. Switch off the ML700.
- 2. Take off the REAR PANEL.
- 3. Mark the position of the DRAIN HOLE and drill a hole with a 10 mm DRILL BIT.




figure 1

- 4. Place the COVER PLATE above the DRAIN HOLE. It is equipped with 2 self adhesive strips and is used as a light shield.
- 5. Clean the TERMINAL HOUSING of any grease. Stick the self adhesive VELCRO STRIP onto the MAINS TERMINAL HOUSING. Remove PCB A16 with its complete housing from the BASE PLATE and stick it onto the VELCRO STRIP on the MAINS TERMINAL HOUSING. Secure PCB A16 with a WIRE TIE. Route it through the COVER of the TERMINAL HOUSING.
- 6. Circle No 20 on the MODIFICATION LABEL.

1	2	3	4	5	6	7	8	9	10	11
12	13	14	15	16	17	18	19	20	21	
22	23	24	25	26	27	28	29	30	31	32
33	34	35	36	37	38	39	40	41	42	

figure 2

7. Mount the REAR PANEL.



CUSTOMER EQUIPMENT SERVICES KODAK AG STUTTGART GERMANY